

**PRV**PATENT- OCH REGISTRERINGSVERKET  
Patentavdelningen

EJV

SE 99/210

REC'D 23 MAR 1999

WFO

PCT

**Intyg  
Certificate**

Härmed intygas att bifogade kopior överensstämmer med de handlingar som ursprungligen ingivits till Patent- och registreringsverket i nedannämnda ansökan.

This is to certify that the annexed is a true copy of the documents as originally filed with the Patent- and Registration Office in connection with the following patent application.

**09/622523**

(71) Sökande                      Telia AB, Farsta SE  
Applicant (s)

(21) Patentansökningsnummer    9801150-5  
Patent application number

(86) Ingivningsdatum                      1998-04-01  
Date of filing

(30) Prioritet begärd från            1998-02-21 SE 9800539-0

Stockholm, 1999-03-08

För Patent- och registreringsverket  
For the Patent- and Registration Office

*Evy Morin*  
Evy Morin

Avgift  
Fee

**PRIORITY  
DOCUMENT**

SUBMITTED OR TRANSMITTED IN  
COMPLIANCE WITH RULE 17.1(a) OR (b)

Improvements in, or Relating to, VDSL

5 The present invention relates to a method of using VDSL zipper duplex transmission in an unsynchronised mode, a system employing VDSL zipper duplex transmission, in an unsynchronised mode, over a common twisted pair cable, a transmission system employing the method, a receiver for use with the transmission system, a transmitter for use with the transmission system and a modem, incorporating a receiver and transmitter, for use with the transmission system.

10 In our co-pending patent application WO 9706619, there is described a procedure for suppressing near-end crosstalk (NEXT) when using duplex communication, in twisted pair wire networks, in which different sub-carriers are used in the two transmission directions, and in which the subcarriers are orthogonal. Preferably a number of sub-carriers are transmitted in each transmission direction. Alternate sub-carriers are used in each direction. The number of sub-carriers used in one transmission direction may be greater than the number used in the other  
15 transmission direction.

20 In our co-pending patent application, referenced above, the use of Zipper VDSL with time synchronization is described. The present invention complements the earlier invention, in that it enables VDSL Zipper duplex transmission, as described in our co-pending patent application, without time synchronization between different modem pairs over the same twisted copper pair cable, i.e. in the same binder group.

25 Zipper is a time-synchronized frequency division duplex implementation of discrete multi tone (DMT) modulation. Two communicating Zipper modems transmit DMT symbols simultaneously with a common clock. The Zipper scheme implies that every carrier, in the total set of carriers in the DMT signal, is exclusively chosen to be used for either for the up-stream, or the down-stream, direction. When all transmitters are time synchronized, the near end cross-talk (NEXT) and near end echoes, injected into the received signal, are orthogonal to the desired signal. To ensure the orthogonality between the signal and all the noise sources

- 2 -

originating from DMT signals in the opposite direction, the guard time, with cyclic extension of the symbols between consecutive symbols, must be dimensioned for the maximum propagation delay of the channel. Further, the size of the guard time is minimised by applying timing advance.

5           Several duplex VDSL systems may share the same twisted pair copper cable. Such systems are referred to as belonging to the same binder group. VDSL systems, using Zipper, which belong to the same binder group, are affected by line attenuation, near end echo and crosstalk. In known Zipper transmission systems, when timing advance is used, all transceivers, in a binding group, start the  
10           transmission of each frame at the same time.

There are three types of signal that affect the length of the cyclic extension in each frame:

- the received signal;
- the echo signal caused by imperfect balance of the hybrid and  
15       impedance discontinuities in the line; and
- the NEXT signal.

Orthogonality, between the received signal, the echo signal and the NEXT signal, is preserved if each sampled DMT symbol is disturbed by a single frame from each one of the near-end transmitters. Because of this, in order to preserve orthogonality, the cyclic extension has to be dimensioned to cover all impulse  
20       responses from the line, the echoes and the NEXT.

25       However, in certain situations it may be difficult, for practical reasons, or otherwise undesirable, to provide and maintain time synchronization between all transmitters in the same binder group. It is therefore desirable to enable Zipper modems, if necessary, to operate in a non-synchronized mode. In other words, only pairwise synchronisation is maintained between a VTU-O and VTU-R pair. The present invention provides this option for Zipper modems and systems employing

- 3 -

Zipper modems. Thus, the present invention permits different users to transmit time asynchronous DMT frames in the same binder group. However, although this is always possible, a noticeable performance penalty can be expected in many situations because of increased NEXT. One way in which the present invention mitigates increased NEXT is by pulse shaping of DMT frames prior to transmission and providing additional pulse shaping at the receiver. Using pulse shaping at the transmitter has the additional advantage of higher suppression of the side lobes of the DMT spectrum. This increases spectral compatibility with other systems, such as, ADSL and CAP-VDSL.

According to a first aspect of the present invention, there is provided a telecommunications transmission system using zipper having at least two VDSL systems, each comprising a pair of zipper modems, said at least two VDSL systems belonging to a binder group common to both VDSL systems, characterised in that said telecommunications transmission system is adapted to:

- handle zipper transmissions transmitted in said binder group;
- at least partly mitigate NEXT; and
- permit transmissions in a first VDSL system which are asynchronous with transmissions in at least a second VDSL system.

DMT frames may be pulse shaped prior to transmission.

Said pulse shaping may produces an improved suppression of side lobes of said DMT's spectrum.

A cyclic extension may be added to DMT symbols, said cyclic extension comprising:

- a suffix which is greater than, or equal to, a channel's propagation delay; and

- 4 -

- a prefix which is greater than, or equal to, a guard time needed to eliminate inter-symbol interference.

Said pulse shaping may be produced by forming pulse shaped wings on a DMT frame in cyclic extensions of the DMT frame.

5 Said pulse shaped wings may be in the form of a raised cosine pulse.

Said pulse shaping may be performed at a transmitter, after addition of a cyclic prefix and cyclic suffix, to a symbol and prior to digital to analogue conversion.

A DMT signal received by a receiver may be windowed to further reduce NEXT.

10 Said windowing may be performed by:

- multiplying  $\mu$  samples at the beginning and end of a block of  $2N+\mu$  samples;
- folding and adding  $\mu/2$  samples from the beginning of the  $2N+\mu$  block of samples to the end of the  $2N$  remaining samples; and
- folding and adding  $\mu/2$  samples from the end of the  $2N+\mu$  block of samples to the beginning of the  $2N$  remaining samples.

15

The same number of sub-carriers may be used for transmission in the up stream direction as are used for transmission in the down stream direction.

A different number of sub-carriers may be used for transmission in the up stream and down stream directions.

20

According to a second aspect of the present invention, there may be provided, in a telecommunications transmission system using zipper and having at least two VDSL systems, each comprising a pair of zipper modems, said at least

- 5 -

two VDSL systems belonging to a single binder group common to both VDSL systems, a method of transmission characterised by permitting zipper transmissions of said first and, at least, said second VDSL transmission systems, to be transmitted in said single binder group, where transmission in said first VDSL system are asynchronous with zipper transmission in said second VDSL system and in which the effects of NEXT are, at least partly, mitigated.

DMT frames may be pulse shaped prior to transmission.

Said pulse shaping may produce an improved suppression of side lobes of said DMT's spectrum.

A cyclic extension may be added to DMT symbols, said cyclic extension comprising:

- a suffix which is greater than, or equal to, a channel's propagation delay; and
- a prefix which is greater than, or equal to, a guard time needed to eliminate inter-symbol interference.

Pulse shaped wings may be formed on a DMT frame in the cyclic extensions of the DMT frame.

Said pulse shaped wings may be formed as a raised cosine pulse.

Said pulse shaping may be performed at a transmitter after addition of a cyclic extension to a symbol and prior to digital to analogue conversion.

A DMT signal received by a receiver may be windowed to further reduce NEXT.

The following steps may be used to perform said windowing:

- multiplying  $\mu$  samples at the beginning and end of a block of  $2N+\mu$

samples;

- folding and adding  $\mu/2$  samples from the beginning of the  $2N+\mu$  block of samples to the end of the  $2N$  remaining samples; and
- folding and adding  $\mu/2$  samples from the end of the  $2N+\mu$  block of samples to the beginning of the  $2N$  remaining samples.

5

The same number of sub-carriers may be transmitted in both an upstream and down stream direction.

A different number of sub-carriers transmitted in the up stream and down stream directions.

10

According to a third aspect of the present invention, there is provided a transmitter, for use in a transmission system as set forth in any preceding paragraph, characterised in that said transmitter comprises an a b-bit buffer and encoder for receiving an input bit stream at a rate of  $R$  bit/s, a n-point IDFT processor for receiving an output from said b-bit buffer and encoder, extension means for adding a cyclic extension to an output of said IDFT processor, a pulse shaper for shaping a DMT symbol output from said extension means, and a digital to analogue converter and low pass filter for converting a DMT symbol received from said pulse shaper to analogue form and passing said DMT to a transmission channel.

15

20

Said pulse shaper may form pulse shaped wings on said DMT symbol as raised cosine pulses.

25

According to a fourth aspect of the present invention, there is provided a receiver, for use in a transmission system as set forth in any preceding paragraph, characterised in that said receiver includes an analogue to digital converter for digitising a DMT symbol received from a transmission channel, a windowing unit connected to an output of said analogue to digital converter, a stripper unit for removing cyclic extensions to said DMT symbol, an n-point DFT processor for

- 7 -

receiving an output from said stripper unit, a frequency domain equalisation unit for receiving an output from said n-point DFT unit and decoder, and a b-bit buffer for receiving an output from said frequency domain equalisation unit and outputting a bit stream at R bit/s.

5

Said windowing unit may perform the following operations:

- multiplying  $\mu$  samples at the beginning and end of a block of  $2N+\mu$  samples;
- folding and adding  $\mu/2$  samples from the beginning of the  $2N+\mu$  block of samples to the end of the  $2N$  remaining samples; and
- 10 - folding and adding  $\mu/2$  samples from the end of the  $2N+\mu$  block of samples to the beginning of the  $2N$  remaining samples.

15

According to a fifth aspect of the present invention, there is provided a modem, for use in a transmission system as set forth in any preceding paragraph, characterised in that said modem includes a transmitter as set forth in any preceding paragraph.

Said modem may include a receiver, as set forth in any preceding paragraph.

Embodiments of the invention will now be described, by way of example, with reference to the accompanying drawings, in which:

20

Figure 1 illustrates the generation of interference signals, cross-talk and echo, that affect the orthogonality of Zipper.

Figure 2 illustrates sampling, at the VTU-O side, of a received frame disturbed by frames from near end transmitters.

Figure 3 illustrates a DMT transmitter/receiver pair for down-stream



transmission, exemplifying symmetric communication where every second sub-carrier is used, respectively, for the up (u), and down-stream (d), directions.

Figure 4 illustrates the frame format for zipper.

Figure 5 illustrates non-orthogonal NEXT.

Figure 6 illustrates pulse shaping of the DMT frame.

Figure 7 is a schematic illustration of the pulse shaping process in the transmitter and the windowing process in the receiver.

Figure 8 illustrates windowing of a received DMT frame.

Figure 9 illustrates asynchronous non-orthogonal NEXT with and without windowing and pulse shaping.

To fully appreciate the operation of the present invention it is necessary to consider the invention disclosed in our earlier co-pending patent application WO 9706619. As previously explained, the present invention enables Zipper to be used in a manner in which VDSL systems operating in the same binder group can operate without mutual synchronisation between each system.

Zipper, as disclosed in our co-pending patent application WO 9706619, is a time-synchronized frequency-division duplex implementation of discrete multi tone (DMT) modulation. Two communicating Zipper modems transmit DMT symbols simultaneously with a common clock. The Zipper scheme implies that every carrier, in the total set of carriers in the DMT signal, is selected for use in either the up-stream, or the down-stream, direction. When all transmitters are time synchronized, the near end cross-talk (NEXT) and near end echoes injected into the received signal, are orthogonal to the desired signal. To ensure that orthogonality is maintained between the signal and all the noise sources, originating from DMT signals in the opposite direction, the guard time with cyclic extension of the symbols,

- 9 -

between consecutive symbols, must be dimensioned for the maximum propagation delay of the channel. Further, the size of the guard time is minimized by applying timing advance.

Figure 1 depicts how two VDSL systems, sharing the same cable, i.e. in the same binder group, are affected by line attenuation, near end echo and cross-talk. Sources of interference that can be identified include:

- echo generated within the hybrids and passed from the transmitters to the receivers;
- NEXT which passes between the transmitter - receiver pairs at the near end; and
- FEXT which passes between the transmitter - receiver pairs at the far end and is transmitted over the full cable length.

When timing advance is used, all transceivers start the transmission of each frame at the same time. There are three types of signals that affect the length of the cyclic extension in each frame: the received signal, the echo-signal due to imperfect balance of the hybrid and impedance discontinuities in the line, and finally the NEXT signal. Figure 2 shows sampling at the VTU-O side of received frame disturbed by frames from near-end transmitters.

As can be seen from Figure 2, the orthogonality between the desired part of the received signal and the disturbances (interference signals) is preserved if each sampled DMT symbol is disturbed by a single frame from each one of the near-end transmitters. As a consequence, to preserve orthogonality, the cyclic extension has to be dimensioned to cover all impulse responses from the line, the echoes, and the NEXT.

The management of the capacity split between up-stream and down-stream is performed by assigning individual carriers for both directions. For example, if a fully symmetric service is required, sub-carriers with even indices can be assigned

to the up-stream and sub-carriers with odd indices can be assigned to the down-stream. Similarly, for an asymmetric 8:1 split, each ninth carrier can be assigned to the up-stream and the other carriers assigned to the down-stream. However, for the sake of spectral compatibility with other existing and future systems, operating on the same cable, alternative carrier assignments can be used.

The transmission and reception of symbols is performed simultaneously at both ends by the VTU-O and by the VTU-R. For down-stream transmission the bit stream is encoded by the VTU-O transmitter into a set of quadrature amplitude modulated (QAM) sub-symbols, where each QAM sub-symbol represents a number of bits determined by the signal-to-noise ratio (SNR) of its associated down-stream sub-channel, the desired overall error probability, and the target bit rate. The set of sub-symbols is then input, as a block, to a complex-to-real discrete Fourier transform (IDFT) processor, see Figure 3. Following the IDFT, a cyclic prefix is added to the output samples to eliminate intersymbol interference, and a cyclic suffix is appended to the output samples to maintain orthogonality between the desired signal and near-end distorting signals. The result is then converted from digital to analog format and applied to the channel.

Thus, the input bit stream, see Figure 3, enters a b-bit buffer and encoder, from which its is passed to the N-point IDFT processor and thence to the cyclic extension adder. Following which the signal is passed via the DAC and lowpass filter to the channel.

At the VTU-R receiver, after analog-to-digital conversion, the cyclic prefix and suffix are stripped, and the samples are transformed back to the frequency domain by a DFT. Each output value used for down-stream transmission is then scaled by a single complex number to compensate for the magnitude and the phase of each down-stream sub-channel's attenuation, and a detector decodes the resulting symbols. The multiplication with this set of complex numbers, one per down-stream sub-channel, is called frequency-domain equalization (FEQ). Figure 3 shows a block diagram of a DMT transmitter and receiver pair, assuming a noiseless channel.

- 11 -

In the steady-state, the subchannel SNRs are monitored in a data-driven manner by the VTU-R during down-stream symbol periods, and the bit distribution is modified, as necessary, at the VTU-O, to optimize system performance. Upon detecting a degradation, or improvement, in one, or more, sub-channel SNRs, the VTU-R computes a modified bit distribution that better meets the desired error performance. Depending on the SNR of a degraded sub-channel, some, or all, of its bits may be moved, via a bit swap algorithm, to one, or more, other sub-channels that can support additional bits. The bit distribution change is reported to the VTU-O, where it is implemented.

For up-stream transmission, the roles of the VTU-O and VTU-R are reversed, that is, transmission and reception are performed on the up-stream set of sub-channels and the operations described above are the same.

The frequency range from zero to 11.04 MHz is partitioned into 2,048 sub-channels. The Nyquist carrier (sub-channel 2,048) and the dc carrier (sub-channel 0) are not be used for data.

Transmission may occur on up to 2047 sub-carriers, although those sub-carriers overlapping the POTS, ISDN, and amateur radio frequency bands are typically not used in the default configuration. The lowest sub-channel available to support data transmission is dependent on the POTS/ISDN splitter design.

The frame format for Zipper comprises two parts, namely:

- the DMT symbol; and
- the cyclic extension.

Orthogonality is maintained between the received signal and interfering DMT signals transmitted in the opposite direction, if they are sufficiently aligned in time. This requirement is fulfilled by the addition of a cyclic extension to the DMT symbol and the use of timing advance (TA). For the ease of description, the cyclic extension can be divided into a cyclic prefix and a cyclic suffix, where:

- 12 -

- the suffix is greater than, or equal to, the propagation delay of the channel; and
- the prefix is greater than, or equal to, the guard time needed to eliminate inter-symbol interference.

Figure 4 illustrates the frame format for zipper.

When timing advance is used all transmitters commence transmission at the same time. The suffix part of the cyclic extension can be treated as an extra guard time required to maintain orthogonality between the up and down-stream channels along the wire line. To fulfil the orthogonality requirement at the receiver, the cyclic extension (prefix + suffix) must also cover the impulse response of the NEXT and the echo signal.

The first  $L_{cs}$  samples of the IDFT output are appended to the block of 4096 time-domain samples  $x_k$ . The last  $L_{cp}$  samples of the IDFT output are prepended to the block. The frame of samples is then read out to the digital-to-analog converter (DAC), see Figure 3, in sequence. That is, the subscripts  $k$  of the DAC samples in the sequence are  $(4096-L_{cp}), \dots, 4095, 0, 1, \dots, 4094, 0, 1, \dots, (L_{cs} - 1)$ .

The length of the cyclic extension ( $L_{cp}$  and  $L_{cs}$ ) is typically a programmable entity set by the network operator.

In order to maximize high duplex efficiency, timing advance can be used so that the VTU-O transmitters and the VTU-R transmitters start transmitting each DMT frame at the same time. During the reception, a DMT symbol is only disturbed by single symbols, not affected by IFI, in the other direction due to the cyclic extension.

Zipper is a duplexing scheme based on the Discrete Multitone Modulation (DMT) line-coding technique and was invented at Telia Research in 1995. A patent application, SE 952775 (corresponding to WO9706619) was filed on 4<sup>th</sup> August 1995.

- 13 -

In certain situations, it may be difficult for practical reasons, or it may be undesirable, to provide and maintain time synchronization between all transmitters in the same binder group. It is therefore desirable to provide an option for Zipper modems which enables them to operate in a non-synchronized mode, where only pairwise synchronization is maintained between a VTU-O and VTU-R pair. Thus, the present invention allows different users to transmit time-asynchronous DMT frames in the same binder group. However, although this is always possible, a noticeable performance penalty, due to increased NEXT, is to be expected in many situations. One possible method of mitigating this is to use pulse shaping of the DMT frames prior to transmission and additional pulse shaping in the receiver. The use of pulse shaping at the transmitter results in a higher suppression of the side lobes of the DMT signal spectrum and gives higher spectral compatibility with other systems, for example, ADSL and CAP-VDSL.

When different pairs of transceivers (modems) operating in the same binder group are asynchronous, interference from NEXT will be introduced, because, the NEXT becomes non-orthogonal and therefore degrades the performance. The reason for the NEXT becoming non-orthogonal is that the received and sampled DMT frame will include NEXT from two consecutive DMT frames which are discontinuous, as depicted in Figure 5.

In order to be able to operate in a non-synchronized mode it is necessary to suppress the NEXT by narrowing its out-of-band spectrum which interferes with the spectrum of the received signal. This can be effected by pulse shaping the DMT frame before transmission.

Pulse shaping a DMT frame is performed by forming pulse-shaped wings, e.g. from a raised cosine pulse, in the cyclic extensions of the frame as shown in Figure 6.

With pulse shaping a continuous phase is created between succeeding frames which suppresses the NEXT-interfering sub-carriers' side lobes.

The pulse shaping operation is performed at the transmitter after the cyclic extension is added to the symbol and before the digital to analog conversion (DAC) is performed. The position of the pulse shaping unit is depicted in Figure 7 which shows a block diagram of a transceiver/modem according to the present invention. The construction and operation of a VDSL modem will be immediately apparent to those skilled in the art from, Figure 7, without further explanation. However, for the sake of completeness a brief description of Figure 7 is set out below.

The transmitter arm of the modem is shown at the top of Figure 7. The input bit stream, at Rbits/s, is passed to a n-bit buffer and encoder from whence a parallel signal,  $X_{d1,k}, X_{u2,k} = 0, \dots, X_{dN-1,k}, X_{uN,k} = 0$ , is passed to an n-point IDFT processor. The output from the IDFT processor,  $x_{1,k}, x_{2,k}, \dots, x_{N,k}$ , is then passed to a unit, P/S, where the cyclic extensions, both prefix and suffix, are added to the DMT symbol. The DMT symbol with cyclic extensions then passes to a pulse shaping unit where the pulse is shaped as described above. The DMT symbol is then passed to a digital to analogue convertor and low pass filter and thence to the transmission channel.

The receiver arm of the modem is shown at the bottom of Figure 7. An incoming signal from the channel is first passed, via a low pass filter and analogue to digital convertor, to a windowing unit, see below for further details. The symbols are then passed to a stripper unit which strips off the cyclic extensions, both prefix and suffix, and thence, as a signal  $y_{1,k}, y_{2,k}, \dots, y_{N,k}$ , to a n-point DFT processor. The signal,  $Y_{d1,k}, Y_{u2,k}, \dots, Y_{dN-1,k}, Y_{uN,k}$ , is then passed to a frequency domain equaliser, FEQ, see the description of Figure 3, and thence to a decoder and n-bit buffer, as a signal  $X_{d1,k}, X_{u2,k}, \dots, X_{dN-1,k}, X_{uN,k}$ , which outputs the received data stream at R bits/s.

Windowing the received DMT frame, as shown in Figure 8, further suppresses the non-orthogonal NEXT. The windowing is performed by multiplying  $\mu$  samples, at both the beginning and end of the  $2N+\mu$  block of samples. The  $\mu/2$  samples from both ends are folded and added to the  $2N$  remaining block of samples at the opposite ends as shown in Figure 8. As with the pulse shaping of

- 15 -

the DMT frames in the transmitter, the windowing in the receiver creates a continuous phase of the non orthogonal NEXT signals. The positioning of the windowing is shown in Figure 8.

5 Figure 9 shows the combined effect, on the non-orthogonal NEXT, of pulse shaping the DMT-frame in the transmitter and windowing the received frame in the receiver. Figure 9 also shows the signal energy, the NEXT reference signal without pulse-shaping and windowing, the NEXT signal after pulse-shaping and windowing and the FEXT signal at each sub-carrier. As seen in the figure, more than 25 dBm/Hz further suppression can be obtained by both pulse shaping and windowing.



## CLAIMS

1. A telecommunications transmission system using zipper having at least two VDSL systems, each comprising a pair of zipper modems, said at least two VDSL systems belonging to a binder group common to both VDSL systems, characterised in that said telecommunications transmission system is adapted to:

- handle zipper transmissions transmitted in said binder group;
- at least partly mitigate NEXT; and
- permit transmissions in a first VDSL system which are asynchronous with transmissions in at least a second VDSL system.

2. A telecommunications system, as claimed in claim 1, characterised in that DMT frames are pulse shaped prior to transmission.

3. A telecommunications system, as claimed in claim 2, characterised in that said pulse shaping produces an improved suppression of side lobes of said DMT's spectrum.

4. A telecommunications system as claimed in either claim 2, or claim 3, characterised in that a cyclic extension is added to DMT symbols, said cyclic extension comprising:

- a suffix which is greater than, or equal to, a channel's propagation delay; and
- a prefix which is greater than, or equal to, a guard time needed to

- 17 -

eliminate inter-symbol interference.

5. A telecommunications system, as claimed in claim 4, characterised in that said pulse shaping is produced by forming pulse shaped wings on a DMT frame in cyclic extensions of the DMT frame.

6. A telecommunications system, as claimed in claim 5, characterised in that said pulse shaped wings are in the form of a raised cosine pulse.

7. A telecommunications system, as claimed in any of claims 4 to 6, characterised in that said pulse shaping is performed at a transmitter, after addition of a cyclic prefix and cyclic suffix, to a symbol and prior to digital to analogue conversion.

8. A telecommunications system, as claimed in any of claims 1 to 7, characterised in that a DMT signal received by a receiver is windowed to further reduce NEXT.

9. A telecommunications system, as claimed in claim 8, characterised in that said windowing is performed by:

- multiplying  $\mu$  samples at the beginning and end of a block of  $2N+\mu$  samples;
- folding and adding  $\mu/2$  samples from the beginning of the  $2N+\mu$  block of samples to the end of the  $2N$  remaining samples; and
- folding and adding  $\mu/2$  samples from the end of the  $2N+\mu$  block of samples to the beginning of the  $2N$  remaining samples.

10. A telecommunications system, as claimed in any previous claim, characterised in that the same number of sub-carriers are used for transmission in the up stream direction as are used for transmission in the down stream direction.

11. A telecommunications system, as claimed in any of claims 1 to 9, characterised in that a different number of sub-carriers are used for transmission in the up stream and down stream directions.

12. In a telecommunications transmission system using zipper and having at least two VDSL systems, each comprising a pair of zipper modems, said at least two VDSL systems belonging to a single binder group common to both VDSL systems, a method of transmission characterised by permitting zipper transmissions of said first and, at least, said second VDSL transmission systems, to be transmitted in said single binder group, where transmission in said first VDSL system are asynchronous with zipper transmission in said second VDSL system and in which the effects of NEXT are, at least partly, mitigated.

13. A method, as claimed in claim 12, characterised by pulse shaping DMT frames prior to transmission.

14. A method, as claimed in claim 13, characterised by said pulse shaping producing an improved suppression of side lobes of said DMT's spectrum.

15. A method, as claimed in either claim 13, or claim 14, characterised by adding a cyclic extension is to DMT symbols, said cyclic extension comprising:

- a suffix which is greater than, or equal to, a channel's propagation delay; and
- a prefix which is greater than, or equal to, a guard time needed to eliminate inter-symbol interference.

- 19 -

16. A method as claimed in claim 15, characterised by forming pulse shaped wings on a DMT frame in the cyclic extensions of the DMT frame.

17. A method as claimed in claim 16, characterised by forming said pulse shaped wings as a raised cosine pulse.

18. A method as claimed in any of claims 14 to 17, characterised by performing said pulse shaping at a transmitter after addition of a cyclic extension to a symbol and prior to digital to analogue conversion.

19. A method as claimed in any of claims 12 to 18, characterised by windowing a DMT signal received by a receiver to further reduce NEXT.

20. A method as claimed in claim 19, characterised by using the following steps to perform said windowing:

- multiplying  $\mu$  samples at the beginning and end of a block of  $2N+\mu$  samples;
- folding and adding  $\mu/2$  samples from the beginning of the  $2N+\mu$  block of samples to the end of the  $2N$  remaining samples; and
- folding and adding  $\mu/2$  samples from the end of the  $2N+\mu$  block of samples to the beginning of the  $2N$  remaining samples.

21. A method as claimed in any of claims 12 to 20, characterised by transmitting the same number of sub-carriers in both an upstream and down stream direction.

22. A method, as claimed in any of claims 12 to 20, characterised by transmitting a different number of sub-carriers in the up stream and down stream

directions.

23. A transmitter, for use in a transmission system as claimed in any of claims 1 to 11, characterised in that said transmitter comprises an a b-bit buffer and encoder for receiving an input bit stream at a rate of R bit/s, a n-point IDFT processor for receiving an output from said b-bit buffer and encoder, extension means for adding a cyclic extension to an output of said IDFT processor, a pulse shaper for shaping a DMT symbol output from said extension means, and a digital to analogue converter and low pass filter for converting a DMT symbol received from said pulse shaper to analogue form and passing said DMT to a transmission channel.

24. A transmitter, as claimed in claim 23, characterised in that said pulse shaper forms pulse shaped wings on said DMT symbol as raised cosine pulses.

25. A receiver, for use in a transmission system as claimed in any of claims 1 to 11, characterised in that said receiver includes an analogue to digital converter for digitising a DMT symbol received from a transmission channel, a windowing unit connected to an output of said analogue to digital converter, a stripper unit for removing cyclic extensions to said DMT symbol, an n-point DFT processor for receiving an output from said stripper unit, a frequency domain equalisation unit for receiving an output from said n-point DFT unit and decoder, and a b-bit buffer for receiving an output from said frequency domain equalisation unit and outputting a bit stream at R bit/s.

26. A receiver, as claimed in claim 25, characterised in that said windowing unit performs the following operations:

- multiplying  $\mu$  samples at the beginning and end of a block of  $2N+\mu$  samples;
- folding and adding  $\mu/2$  samples from the beginning of the  $2N+\mu$  block of samples to the end of the  $2N$  remaining samples; and

- 21 -

- folding and adding  $\mu/2$  samples from the end of the  $2N+\mu$  block of samples to the beginning of the  $2N$  remaining samples.

27. A modem, for use in a transmission system as claimed in any of claims 1 to 11, characterised in that said modem includes a transmitter as claimed in either claim 23, or 24.

28. A modem, as claimed in claim 27, characterised in that said modem includes a receiver, as claimed in either claim 25, or 26.

**ABSTRACT**

**Improvements In, or Relating to, VDSL**

Zipper is a time-synchronized frequency-division duplex implementation of discrete multi tone (DMT) modulation. Two communicating Zipper modems transmit DMT symbols simultaneously with a common clock. The Zipper scheme implies that every carrier, in the total set of carriers in the DMT signal, is exclusively chosen to be used for either the up-stream or the down-stream direction. When all transmitters are time synchronized, the near end cross-talk (NEXT) and near end echoes injected into the received signal are orthogonal to the desired signal.

The present invention provides a telecommunications transmission system using zipper and having at least two VDSL systems. Each of VDSL system comprises a pair of zipper modems communicating over a cable transmission path. The two VDSL systems employ a common cable. The telecommunications transmission system is adapted to:

- handle zipper transmissions transmitted over the common cable;
- at least partly mitigate NEXT; and
- permit transmissions in a first VDSL system which are asynchronous with transmissions in a second VDSL system.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
21

1/9




FIGURE 1






FIGURE 2




FIGURE 3




FIGURE 4




FIGURE 5




FIGURE 6




FIGURE 7




FIGURE 8




FIGURE 9